



| Fluor-E-lux® - Bateria 6Vx4Ah | | |
|--------------------------------------|--------------------------|------------------------|
| Lâmpada (W) | Autonomia Aprox. (Horas) | Fluxo Total Aprox. (%) |
| 1x9 | 03:00 | 85 |
| 1x11 | 02:00 | 75 |
| 1x16 | 02:30 | 50 |
| 1x18D | 02:00 | 50 |
| 1x20 | 02:00 | 40 |
| 1x26 | 01:30 | 35 |
| 1x32 | 01:30 | 30 |
| 1x40 | 01:30 | 20 |
| 1x65 | 01:00 | 20 |
| 1x110 | 01:30 | 10 |
| 2x9 | 01:30 | 50 |
| 2x11 | 01:30 | 50 |
| 2x16 | 01:30 | 30 |
| 2x20 | 01:30 | 25 |
| 2x32 | 01:00 | 20 |
| 2x40 | 01:30 | 15 |

| Fluor-E-lux® - Bateria 12Vx7Ah | | |
|---------------------------------------|--------------------------|------------------------|
| Lâmpada (W) | Autonomia Aprox. (Horas) | Fluxo Total Aprox. (%) |
| 1x14 | 03:00 | 90 |
| 1x20 | 02:00 | 100 |
| 1x26 | 01:00 | 100 |
| 1x32 | 01:00 | 100 |
| 1x36 | 01:00 | 95 |
| 1x40 | 01:00 | 95 |
| 1x58 | 01:00 | 65 |
| 1x65 | 01:00 | 60 |
| 1x110 | 01:00 | 30 |
| 2x14 | 01:00 | 100 |
| 2x16 | 01:00 | 75 |
| 2x20 | 02:00 | 55 |
| 2x32 | 01:00 | 60 |
| 2x36 | 01:00 | 45 |
| 2x40 | 01:00 | 40 |
| 2x58 | 01:00 | 30 |
| 2x65 | 01:00 | 30 |

| Fluor-E-Lux® -NICD Bateria 3,6V | | |
|--|--------------------------|------------------------|
| Lâmpada (W) | Autonomia Aprox. (Horas) | Fluxo Total Aprox. (%) |
| 1x9 | 02:30 | 70 |
| 1x11 | 02:30 | 60 |
| 1x14 | 02:30 | 50 |
| 1x16 | 02:30 | 40 |
| 1x20 | 02:30 | 35 |
| 1x32 | 01:30 | 23 |
| 1x36 | 01:30 | 20 |
| 1x40 | 02:30 | 15 |
| 1x58 | 01:30 | 14 |
| 1x65 | 01:30 | 10 |
| 1x85 | 01:30 | 10 |
| 1x110 HO | 01:00 | 10 |
| 1x26 D/E | 01:30 | 30 |
| 1x32 T/E | 01:30 | 25 |
| 1x36 T/E | 02:00 | 20 |
| 1x42 T/E | 01:30 | 20 |
| 2x9 | 02:00 | 40 |
| 2x11 | 01:30 | 40 |
| 2x14 | 01:30 | 30 |
| 2x16 | 01:30 | 25 |
| 2x20 | 01:30 | 20 |
| 2x32 | 01:00 | 15 |
| 2x36 | 02:00 | 10 |
| 2x40 | 01:30 | 10% |
| 2x58 | 01:00 | 10% |